



-
-
-

-
-
-

- Telcordia GR-1209-CORE
- Telcordia GR-1221-CORE

	nm	1525~1568
		1/99~50/50
		Panda fiber
	dB	>50
	dB	>55
	dB	>18
		-5 +65
		-40 +85

	IL Tap	IL Signal
30/70	6.1	2.3
40/60	4.9	2.9
50/50	3.8	3.8

	A	B	A35	
(mm)	3×48	3×55mm	3×35	90×16×9
(mm)				49.9×9.3×2 3.0

WBC-□-□-□-□-□-□-□(PM)

- Package A,B,A35,C
- Connector: FC/UPC,FC/APC, SC/UPC,SC/APC,FC/UPC,FC/APC
- Fiber length:00:adapter;1:1m;customized
- Fiber Dia:00:adapter;025: 0.25mm;09: 0.9mm;20: 2.0mm
- Splitting radio:01:1/99; 02:2/98;50:50/50
- Wavelength:1550:1550nm,
- Port:12:1x2; 22:2x2